

# 2D Barcode Scanner Android OS PDA

## OCBS -D5000

□□□

- Android 7.0
- 1GB RAM 16GB ROM
- 5.0" 720 \* 1280
- IP65 / 1.5m
- 3.7V 8000mAh
- 8 MP LED
- 4G / Wifi / GPS /
- HHW SoftwareDevelopment Kit
- 1D / 2D BarcodeScanner
- RFIDL / HF / UHF / NFC
- TCS1SMCapative

□□		
□□□□		
□□	170mmx85mmx23mm±2mm	
□□	380g	
□□	5.0" TFT-LCD 720x1280	
□□	LED	
□□	3TP 64	
□□	2PSAM 1SIM 1TF	
□□	3.7V 4500mAh UHF 8000mAh	
□□□□		
□□□□□	A53 1.5GHz	
□□□□	Android 7.0	
□□	2GB RAM 16GB ROM MicroSD 32GB	
□□□□		
□□□□	-20°C 50°C	
□□□□	-20°C 70°C	
□□	5RH 95RH	
□□□□	5mm/1.5mm	
□□	IP65 IEC	
ESD	±15kv ±8kv ±8kv	
□□□□		
SDK	HHW	
□□	Java	
□□	Android Studio Eclipse	
□□□□		
WWAN	TDD-LTE 38,39,40 FDD-LTE 1,2,3,4,7; WCDMA 850/1900 / 2100MHz; GSM / GPRS / Edge 850/900/1800 / 1900MHz;	
WLAN	2.4G / 5G IEEE 802.11 a / b / g / n / ac	
WPAN	Class v2.1 + EDR v3.0 + HS v4.0	
□□□□□□	GPS A-GPS 5	
□□□□□□		
□□□□□□□□		
1D	□□□□□□	□□□□N431x
□□□□	□□	□□□□□□□□
□□□□	2D CMOS	□□□□N6603
□□	□□	PDF417 MicroPDF417 Com pos ite RSS TLC-39 Datamatrix QR Micro QR Aztec MaxiCode Pos ta Net Pos ta Pos ta Pos ta Pos ta
□□□□□□		
□□□	800	

RFID	RFID LED	
RFID LF		125KHz / 134.2KHz FDX-B / HDX
		ISO 11784 & 11785
	R / W	200010
RFID HF		13.56MHz
		ISO 14443A & 15693
	R / W	20008
RFID UHF		865~868MHz / 920~925MHz
		EPC C1 GEN2 / ISO 18000-6C
		2dB
	R / W	1001.5
2.45GHz		200
433MHz		200
ZigBee		
	IEEE 802.15.4	
		100200
	TCS1SM	
	508 DPI	
	FRR <0.008 FAR <0.005	
	1000	
PSAM		
	ISO 7816	
		9600,19200,38400,43000,56000,57600,115200
		2000000
		1xPower 1x 1xDC 1xUSB
		UHF