

Android4.1

□□ARM Cortex-A9□□1.5G□

WCDMA[CDMA2000[[[

A-GPS

__300____LED_____

SIM__PSAM___SD_TF____

____3.7V 4000mAh___

__4.0___QVGA_____

____IP67_

000601.5000000000

	<u>, </u>
0000	
00	152000L0×77000H0×29000W00
00	<[]
	004.0000QVGA000000
	TFT-LCD[65 480 * 800 QVGA
	LEDODODODO
0000	SIMPSAMSD_TF
0000	USB2.0[][][RS-232[][][]
0000	000000000000000000000000000000000000000
0000	00000003.7V 4000mAh
00	8Ω1W[[[[
00	29pcs[[[[
0000	
	□□ARM Cortex-A9□□1.5G
	2G
□□ROM	004G NAND000
0000	0001EEE802.11b / g00000000000000000000000000000000000
WCDMA	UMTS2100 / 900MHz[]
	UMTS1900 / 850MHz[]
	GSM850 / 900/1800 / 1900MHz[]
CDMA2000	CDMA2000 1X[CDMA2000 EV-DO 0 CDMA2000 EV-DO A
	BC0 800MHz BC1 1900MHz
00	00002.0 + EDR00005-10M
0000	
0000	-20°C∏50°C
0000	-25°C∏70°C
0000	50RH - 950RH00000
0000	
0000	1000D/ 0.5MDDD6DDDDD

0000	IP67
0000	
0000	Android4.1
SDK	
0000	JAVA
0000	
0000 00	
	□□SE655
	5MIL000
	0ft.candles-10000ft.candles
0000	50 /🗆
000	53°±3°
00000	UPC / EAN_EAN_Bookland_128_39_93_11 2 52 525
000000	□□SE955
	4mil
000	10000ft.candles[]107640[][]
0000	104[]±[]12 /[][Bothway[][][][]
000	47°±35°0000/ 35°±3°00000
00000	UPC / EANDOCode12803900CODE930Code1105002000 2 50002 5000000RSS
0000 00	
CMOS[[[]	□□SE4500
000000	752000×4800000000
	□□□□9000ft.candles / 96900 □□□
	□□655nm±10nm□
	PDF417@MicroPDF417@@@RSS@TLC-39@@@@QR@@@QR@@@@MAXICODE;@@@@@ @@POSTNET@@@@@@@@@@@@anPostal@@@@KIX@3
RFID	
LF	125K / 134K; ISO11784 / ISO11785
HF	13.56MHz□; ISO14443A / B □□
	003000000LED0000
000000	□□A-GPS