

Android 7.0 PDA

M / N OCBS -D5000



□□

- Android 7.0
- 2GB RAM □ 16GB ROM
- □□□ 5.0□□ 720 * 1280□□□□□□□□
- □□□ IP65 / 1.5□□□
- □□□□□□□□□ 3.7V□ 4500□ 8000mAh□□
- □□□□□ 8 MP□□ LED□□□□□□□□
- □□ 4G / Wifi / GPS /□□
- HHW□□□□□□
- 1D / 2D□□□□□□□□□□
- RFID LF / HF / UHF / NFC□□□□
- TCS15M□□□□□□□□□□□□

□□	
□□□□	
□□	170□□□□□□ x 85□□□□□□ x 23□□□□□□ ± 2□□
□□	□□□ 380g□□□□□□□□□□
□□	□□□ 5.0□□ TFT-LCD□ 720x1280□□□□□□□□
□□	LED□□
□□	3□□ TP□□ 6□□□□□□ 4□□□

OS	2xPSAM1xSIM1xTF	
OS	3.7V4500mAhUHF800mAh	
OS		
OS	A53 1.5GHz	
OS	Android 7.0	
OS	2GB RAM16GB ROMMicroSD32GB	
OS		
OS	-20°C50°C	
OS	-20°C70°C	
OS	5RH95RH	
OS	5/1.5	
OS	IP65IEC	
ESD	±15kv±8kv±8kv	
OS		
SDK	HHW	
OS	Java	
OS	Android StudioEclipse	
OS		
WWAN	TDD-LTE38,39,40FDD-LTE1,2,3,4,7; WCDMA850/1900 / 2100MHz; GSM / GPRS / Edge 850/900/1800 / 1900MHz;	
WLAN	2.4G / 5GIEEE 802.11 a / b / g / n / ac	
WPAN	Class v2.1 + EDRv3.0 + HSv4.0	
OS	GPSA-GPS5	
OS		
OS		
1D	431x	
OS	2D CMOS	N6603
OS		PDF417MicroPDF417Com pos iteRSSTLC-39DatamatrixQRMicro QR AztecMaxiCodePos talNetPos talPos talPos tal
OS		
OS	800	
OS	LED	
RFID		
RFID LF		125KHz / 134.2KHzFDX-B / HDX ISO 11784& 11785 R / W210
RFID HF		13.56MHz ISO 14443A& 15693 R / W28
RFID UHF		865~868MHz920~925MHz EPC C1 GEN2 / ISO 18000-6C 2dBi R / W11.5
2.45GHz	200	
433MHz	200	
ZigBee		
OS	IEEE 802.15.4	
OS	100200	
OS		
OS	TCS1SM	
OS		
OS	508 DPI	
OS	FRR <0.008FAR <0.005	
OS	1000	
PSAM		
OS	ISO 7816	
OS	9600,19200,38400,43000,56000,57600,115200	

00	20000000
00	
00	1xPower00 1x000000 1xDC000 1xUSB000
000	000000UHF000





OCBS-D5000



http://www.aliexpress.com/store/403448?tracelog = minisite_CI

3.

OCOM

500 100

12 + 1 24

30 DOA DOA

4.

T / T LC Western Union Escrow T / T Western Union Escrow Paypal .Escrow Alipay.com Moneybookers Visa MasterCard Maestro Solo Carte Bleue Pos tePay CartaSi 4B Euro6000

5.

6.

Eruopean

133 1300 O2 500 50

OCOM

500 POS

O2 Star

1500 133

9 OEM / ODM

POS

FCC CE Soncap POA BIS

12 + 1

“”