

Android 5.1 PDA

D4000

Android 5.1;

1G RAM 8G ROM TF 64 GB;

28nm ARM Qual-core A53, 1.3-1.5GHz

4G LTE 3G WCDMA;

GPS A-GPS positioning;

500 LED;

SIM PSAM Micro SD TF;

3.7V 4000mAh;

4.0 QVGA;

IP65;

6 1.5

	157x 76x 28
	324
	4.0 QVGA TFT-LCD 650000 480 * 800 QVGA LED
	SIM Micro SD TF
	USB 2.0
	3.7V 4000mAh
	28nm ARM Qual-core A53, 1.3-1.5GHz
	1G
ROM	8G NAND Micro SD / TF 64G
	IEEE 802.11b / g / n
LTE	FDD-B1 B3 B7 B8 B28 TDD-B38 B39 B40 B41

WCDMA / GSM	WCDMA 850MHZ;824MHZ-849MHZ;869MHZ-894MHZ 900MHZ;880MHZ-915MHZ;925MHZ-960MHZ 1800MHZ;1710MHZ-1785MHZ;1805MHZ-1880MHZ 1900MHZ Uplink;1850MHZ-1910MHZ;1930MHZ-1990MHZ
	2.0 + EDR / 3.0 + HS / 4.1 + HS 5-10m
	-1050
	-2570
	0RH - 95RH
	61.5m
	1000 / 0.5m6
	IP65
	Android5.1
SDK	
	JAVA
	Mingde966;955;HoneywellN4313
	4Mil
	10000ft.candles;107640 lux
	104±12 /
	47±35 / 35±3
	UPC / EAN;Code128;Code39;Code93;Code11;Interleaved 2 of 5;Discrete 2 of 5;Chinese 2 of 5;Codabar;MSI;RSS
CCD	CCD 2D;HONEYWELL N3680;2D
	752×480
	9000ft.candles / 96900
	655nm±10nm
	PDF417;MicroPDF417;Com pos ite;RSS;TLC-39;Datamatrix;QR;Micro QR;Aztec;MaxiCode;Pos;Pos tNet;Pos tal;Pos tal;Pos tal;Pos tal;KIX;3
RFID	
HF	13.56MHz; ISO14443A
	500;LED
	A-GPS