

OCBS-D5000 PDA

OCBS -D5000

Product Description

OCBS

-- Android 7.0

-2GB RAM 16GB ROM

-5.0" 720 * 1280

-IP65 / 1.5m

-3.7V 8000mAh

-8 MP LED

-4G / Wifi / GPS

-SKD

-1D / 2D

-RFIDLF / HF / UHF / NFC

-TCS1 SMC

OCBS	
OCBS	
OCBS	170mm x 85mm x 23mm D ± 2
OCBS	380g
OCBS	5.0" TFT-LCD 720x1280
OCBS	LED
OCBS	3 TP 6 4
OCBS	2 PSAM 1 SIM 1 TF

□□	□□□□□□□□□□3.7V□8000mAh	
□□□□		
□□□□□	□□A53 1.5GHz□□	
□□□□	Android 7.0	
□□	2GB RAM□16GB ROM□MicroSD□□□32GB□□□	
□□□□		
□□□□	-20°C□50°C	
□□□□	-20°C□70°C	
□□	5□RH□95□RH□□□□□	
□□□□	□□□□□□□□□□□□5□□/1.5 m□□□□□□	
□□□□	IP65□□□IEC	
□□□	±15kv□□□□□□±8kv□□□□□□±8kv□□□□□	
□□□□		
□□□	□□□□□□□□	
□□	Java	
□□	Android Studio□Eclipse	
□□□□		
□□□□	TDD-LTE□□38□39□40□FDD-LTE□□1,2,3□4,7; WCDMA□850/1900 / 2100MHz□; GSM / GPRS / Edge 850/900/1800 / 1900MHz□□	
□□□□□□	2.4G / 5G□□□IEEE 802.11 a / b / g / n / ac	
□□□□□□	□□Class v2.1 + EDR□□□v3.0 + HS□□□v4.0	
□□□□□□□	GPS□□□□A-GPS□□□□□□5 m	
□□□□□□		
□□□□□□□□□□		
□□□□□	□□□□□□□□	□□□□N431x
□□□□□	□□□□□	□□□□□□□□□□□
□□□□□	2D CMOS □□	□□□□N6603
□□□□□		PDF417□MicroPDF417□Com pos ite□RSS□TLC-39□Datamatrix□QR□□Micro QR □□Aztec□MaxiCode□Pos tal Codes□□□Pos tNet□□□Planet□□ □□Pos tal□□□□□□Pos tal□□□□Pos tal□□□□
□□□□		
□□□	8.0□□□□□	
□□	□LED□□□□□□□□□□	
RFID□□□□□□□□		
RFID□□	□□	125KHz / 134.2KHz□FDX-B / HDX□
	□□	ISO 11784&11785
	□/□□□	2□□□10□□
RFID□□	□□	13.56MHz□
	□□	ISO 14443A&15693
	□/□□□	2□□□8□□
RFID□□□	□□	865□868MHz□920□925MHz
	□□	EPC C1 GEN2 / ISO 18000-6C
	□□□□	□□□□□□2dBi□
	□/□□□	1 m□1.5 m□□□□□□□□□□□□
□□2.45GHz	□□□□□□□200 m□□□□□□□	
433MHz□	□□□□□□□200 m□□□□□□□	
ZigBee□□□□□□□□		
□□	IEEE 802.15.4□□□□□	
□□□□	100 m□200 m□□□□□□□	
□□□□□□□□□□		
□□□	TCS1SM	
□□□□□	□□□□□□□□□□	

□□□	508 DPI
□□	FRR <0.008 □□ FAR <0.005 □
□□	1000
PSAM □□□□□□□□	
□□	ISO 7816
□□□	9600 □ 19200 □ 38400 □ 43000 □ 56000 □ 57600 □ 115200
□□	2 □□□□□□□□
□□□	
□□	1x □□ 1x □□□□□□□□ 1x DC □□□□ 1x USB □□□□
□□□	□□□□□□ UHF □□□□

▶ Picture Show



OCBS-D5000





OCBS-D5000





OCBS-D5000





OCBS-D5000



▶ Company



▶ Certificates



▶ Payment



▶ Contact us

