

□□□□□□□□□□□□□□□□□□□□

□□□□-D5000□

□□□□□□□□□□□□□□□□□□

□□

- Android 5.1.1
- 1GB RAM□8GB ROM
- □□□5.0□□720 * 1280□□□□□□□□
- □□□IP65 / 1.5□□□□□□
- □□□□□□□□□3.7V□8000mAh□□
- □□□□□8 MP□□□LED□□□□□□□□□□
- □□4G / Wifi / GPS /□□
- HW□□□□□□□□□□
- □□/□□□□□□□□□□□□□□
- RFIDL / HF / UHF / NFC□□□□
- TCS1SM□□□□□□□□□□□□□□

□□□

□□	
□□ □□	
□□	170mm□H□×85mm□W□×23mm□D□±2mm
□□	□ □□□380□□□□□□□□□□□□
□□	□□□ 5.0□□TFT-LCD□720x1280□□□□□□□□□□
□□	LED□□
□□	3 TP □□□6□□□□□□4□□□□□□
□□	2 PSAM□1□SIM□1□TF
□□	□□ □□□□□□□3.7V□8000mAh
□□ CHARACTERSTICS	
□□□□□□	□ A53 1.5GHz□□
□□ □□	Android□ 5.1.1
□□	1GB RAM□8GB ROM□MicroSD□□□32GB□□□
□□ □□	
□□ □□□	-20°C□50°C
□□ □□□	-20°C□70°C
□□	5□RH □95□RH□□□□□□
□□ □□□□	5ft./1.5 m□□□□□□□□□□□□□□□□□□
□□	IP65□ IEC□□□

ESD	±15kv□□□□±8kv□□□□±8kv□□□□	
□□ □□		
SDK	HHW □□□□□□	
□□	Java□	
□□	Android□ □□□□Eclipse	
□□ □□		
WWAN	TDD-LTE□□38,39,40□FDD-LTE□□1,2,3□ 4,7; WCDMA□850/1900 / 2100MHz□□; GSM / GPRS / Edge 850/900/1800 / 1900MHz□;	
WLAN	2.4G / 5G□ □□IEEE 802.11 a / b / g / n / ac	
WPAN	□□ Class v2.1 + EDR□□□v3.0 + HS□□□v4.0	
□□□□□□	GPS□□□□A-GPS□□□□□5□	
□□ CAPTUER		
□□ □□□□□□		
1D □□	1D □□□□	□□□□ N431x
	□□	□□ □□□□□□
2D □□	2D CMOS□□□□	□□□□N6603
	□□	PDF417□MicroPDF417□□□□RSS□ TLC-39□Datamatrix□QR□□Micro QR□□Aztec□MaxiCode□□ □□□□□□ PostNet□□□□□□□□□□□□□□□□□□□□□□ □□
□□ □□		
□□□□	8 □□□□	
□□	□□□□ □LED□□□□	
RFID □□□□□□□□		
RFID LF	□□	□125KHz / 134.2KHz□FDX-B / HDX□
	□□	ISO 11784&□□; 11785
	R / W □□	2□□ □10□□
RFID HF	□□	13.56MHz□
	□□	ISO 14443A&□□; 15693
	R / W □□	2□□ □8□□
RFID □□□□	□□	865□868MHz□□ □□920□925MHz
	□□	EPC C1 GEN2 / ISO 18000-6C
	□□ □□	□ □□□2DBI□
	R / W □□	1□ □1.5□□□□□□□□□□
□□ 2.45GHz□	□ □□□□200□□□□□□	
433MHz□	□ □□□□200□□□□□□	
ZigBee□ □□□□□□□		
□□	IEEE 802.15.4□□□□□	
□ □□	100 □□200□□□□□□	
□□ □□□□□□		
□□□□	TCS1SM	
□□□□ □□	□□□□ □□□□□□	
□□□□	508 DPI	
□□	FRR <0.008□□FAR <0.005□	
□□	1000	
PSAM □□□□□□□□		
□□	ISO 7816	
□□□□	9600□ 19200□38400,43000,56000,57600,115200	
□□	2 □□□□□□	
□□		
□□	1xPower □□ 1x□□□□□□□□ 1xDC □□□□□ 1xUSB □□□□	

□□□

□□□□□ UHF□□□



OCBS-D5000



www.ocominc.com



□□□□□□□□□□□□□□□□□□