

OCBs PDA

M / N OCBs-D5000

□□

Android 5.1.1
 1GB RAM □ 8GB ROM
 □□□ 5.0 □□ 720 * 1280 □□□□□□□□
 □□□ IP65 / 1.5 □□□□
 □□□□□□□□ 3.7V □ 8000mAh □□
 □□□□ 8 MP □□ LED □□□□□□□□
 □□ 4G / Wifi / GPS / □□
 HHW □□□□□□□□
 1D / 2D □□□□□□□□□□
 RFID LF / HF / UHF / NFC □□□□
 TCS1SM □□□□□□□□□□□□□□

□□

□□ □□	
□□	170mm □ H □ × 85mm □ W □ × 23mm □ D □ ± 2mm
□□	□ □□□ 380 □□□□□□□□□□
□□	□□□ 5.0 □□ TFT-LCD □ 720 × 1280 □□□□□□□□
□□	LED □□
□□	3 TP □□□ 6 □□□□□□ 4 □□□□□□
□□	2 PSAM □ 1 □ SIM □ 1 □ TF
□□	□□ □□□□□□ 3.7V □ 8000mAh
□□ CHARACTERSTICS	
□□□□□□	□ A53 1.5GHz □□
□□ □□	Android □ 5.1.1
□□	1GB RAM □ 8GB ROM □ MicroSD □□□ 32GB □□□
□□ □□	
□□ □□□	-20°C □ 50°C
□□ □□□	-20°C □ 70°C
□□	5 □ RH □ 95 □ RH □□□□□□
□□ □□□□	5ft./1.5 m □□□□□□□□□□□□□□□□
□□	IP65 □ IEC □□□
ESD	±15kv □□□□□ □ ±8kv □□□□□ □ ±8kv □□□□□
□□ □□	
SDK	HHW □□□□□□□□
□□	Java □
□□	Android □ Studio □ Eclipse
□□ □□	
WWAN	TDD-LTE □□ 38,39,40 □ FDD-LTE □□ 1,2,3 □ 4,7; WCDMA □ 850/1900 / 2100MHz □□; GSM / GPRS / Edge 850/900/1800 / 1900MHz □;

WLAN	2.4G / 5GDual IEEE 802.11 a / b / g / n / ac	
WPAN	Class v2.1 + EDRv3.0 + HSv4.0	
	GPSA-GPS5	
CAPTUE		
1D	1D	N431x
2D	2DCMOSImager	N6603
		PDF417MicroPDF417RSS TLC-39DatamatrixQR Micro QRAztecMaxiCode PostNet
	8	
		LED
RFID		
RFID		125KHz / 134.2KHzFDX-B / HDX
		ISO 11784&; 11785
	R / W	2 10
RFID HF		13.56MHz
		ISO 14443A&; 15693
	R / W	2 8
RFID		865868MHz 920925MHz
		EPC C1 GEN2 / ISO 18000-6C
		2DBI
	R / W	1 1.5
	2.45GHz	200
	433MHz	200
ZigBee		
		IEEE 802.15.4
		100 200
		TCS1SM
		508 DPI
		FRR <0.008 FAR <0.005
		1000
PSAM		
		ISO 7816
		9600 1920038400,43000,56000,57600,115200
		2
		1xPower 1x 1xDC 1xUSB
		UHF