

433Mhz or Bluetooth Mini Wireless Barcode Scanner with Screen

(Model No.: OCBS-D005/D105)

FEATURE:

- Mini 433Mhz or Bluetooth wireless barcode scanner with screen and memory, convenient and portable;
- Wireless working distance can meet general request, 30 to 300m in open area;
- 4M memory Can store 100,000 barcodes;
- Instantly store and bulk transfer mode, secure to keep the data;
- Auto-turn-off at low voltage, high efficiency and energy saving;
- No need special application software, easy and comfortable operation.



SPECIFICATION:

Wireless Communications:	
Modulation	GFSK
Transmission rate	200Kbps
Power	10dBm
Transmission Distance	Visual straight line distance 300 meters
Antenna	Built-in spring antenna
Performance Characteristics	
Light Source	650nm laser
Supported barcodes	EAN-8, EAN-13,UPC-A, UPC-E, Code 39, Code 93, Code 128, EAN128, Codabar, Industoal 2 of 5,Interleave 2 of 5, Matrix 2 of 5, MSI etc
Scanner Type:	Bi-directional
Scan rate	48±2 scan/second
Scan distance	10-520mm
Scan width	20mm@window, 220mm@200mm
Resolution	0.10mm (pcs0.9)
Depth of Field	0~250mm (0.33mm, PCS 90%)
Working Way	Triggered or automatic (continuous mode) scanning
Physical Characteristics	
Memory:	4M (Can store 100,000 barcodes)
Interfaces:	Standard configuration mini USB receiver; RS232 and PS2 optional
Current:	96mA (working) 46mA(standby)
Battery:	Built-in rechargeable lithium ion battery (3.7V, 1900mAh)
Material	ABS+PC
Dimension:	102mmX46mmX28mm
Weight:	130g (with battery)
User Environment	

Operation Temperature	-20 Degree C~45 Degree C
Storage Temperature	-20 Degree C~60 Degree C
Humidity:	5~95% relative humidity, non-condensing
Safe	
EMI/RFI:	CE & FCC DOC compliance
Safety Standard	The second national laser safety standards
Ordering Information	
OCBS-D005	Mini 433Mhz Wireless Barcode Scanner with screen and memory
OCBS-D105	Mini blue tooth Wireless Barcode Scanner with screen and memory

Tag: Barcode Scanner, Wireless barcode scanner, mini barcode scanner, Data collector, Data Terminal, Industrial PDA, Portable Stock Taking Terminal,