

# 4 POS PDA OCBS -D7000

□□

Android 7.0  
 2GB RAM □ 16GB ROM  
 4.0 □ 480 \* 800 WVGA IPS □  
 1D / 2D □  
 RFID LF / HF / UHF / for optional  
 □□ & □□; Functional Keypads  
 □□ 4G / Wifi / GPS / □□  
 □□□□ 5 MP □ LED □  
 □□□□□□□□ 3.7V □ 5200mAh □  
 □□□□ IP65 / 1.5 mDrop Tolerance

□□

□□□□

□□ 158□□□□□x75□□□□□x28□□□□□±2□□  
 □□ □□□300□□□□□□□□□□  
 □□ 4.0□□TFT-LCD □WVGA 480x800□□□□□□□□  
 □□ LED□□  
 □□ 3□TP□□17□□□□□4□□□□  
 □□ 2□PSAM□1□SIM□□1□TF  
 □□ □□□□□□□□□3.7V□5200mAh

□□□□

□□□□□ Cortex A53□□1.3GHz□□□□  
 □□□□□ Android 7.0  
 □□ 2GB RAM□16GB ROM□MicroSD□□□32GB□□□

□□□□

□□□□ -20°C□50°C  
 □□□□ -20°C□70°C  
 □□ 5□RH□95□RH□□□□□□  
 □□□□ 5□□/1.5□□□□□□□□□□□□□□□□  
 □□ IP65□□□IEC□□  
 ESD ±15kv□□□□□±8kv□□□□□±8kv□□□□□

□□□□

SDK HHW□□□□□□□  
 □□ Java□  
 □□ Android Studio□Eclipse

□□□□

WWAN	WCDMA 850/1900 / 2100MHz GSM / GPRS / Edge 850/900/1800 / 1900MHz	
WLAN	IEEE 802.11 b / g / n	
WPAN	Class v2.1 + EDR v3.0 + HS v4.0	
	GPS A-GPS 5	
1D	N431x	
2D CMOS	N6603	
	PDF417 MicroPDF417 Composite ite RSS TLC-39 Datamatrix QR Micro QR Aztec MaxiCode Postal Net Postal Postal Postal Postal Postal Postal	
	500	
	LED	
<b>RFID</b>		
RFID LF	125KHz / 134.2KHz FDX-B / HDX	
	ISO 11784 & 11785	
	R / W	2 10
		13.56MHz
RFID HF	ISO 14443A & 15693	
	R / W	2 8
<b>PSAM</b>		
	ISO 7816	
	9600,19200,38400,43000,56000,57600,115200	
	2	
	1xPower 1xLithium 1xDC 1xUSB	

**ocom**  
At your side



[www.ocominc.com](http://www.ocominc.com)

