

# OCOM-R20 RFID 13.56MHz USB / PS2 / RS232

Model	W20; R20
Frequency	13.56MHz
Protocol	ISO 14443 TYPE A / ISO15693
Supported Tags	Mifare_One S50& S70 / UltraLight / Mifare_ProX; AT88RF020 / SR176 / SR1X4K / Tag_it2k HF-1 / I.CODE SLI / SRF55V10P
Response Time	< 100ms
Antenna	5 -8
Power	DC 5V
Interface	USB / RS232
Voltage	-10 ~ 70
Current	-20 ~ +80
Temperature	0 ~ 90
Dimensions	10.5 * 7.5 * 1.3
Weight	121g
Software	CSharp Demo / delphi7.0 / VC6.0 / VB / JAVA Demo

## Features

### 1. High Speed

OCOM RFID reader can read 128Kbit tags in 24ms, and can read 1Kbit tags in 10ms.

### 2. Multiple Payment Methods

OCOM RFID reader supports T / T / LC / T / T / Alipay.com / Moneybookers / Visa / MasterCard / Maestro / Solo / Carte Bleue / PostePay / CartaSi / 4B / Euro6000.

### 3. Shipment

OCOM RFID reader is shipped by air.

### 4. Aliexpress & Amazon

OCOM RFID reader is available on Aliexpress and Amazon. Aliexpress: [http://www.aliexpress.com/store/403448?tracelog=minisite\\_C](http://www.aliexpress.com/store/403448?tracelog=minisite_C) / Amazon: <http://www.amazon.com/dp/B000000000>

### 5. After Sales

OCOM RFID reader has 1 year warranty, 24 hours technical support, 3 days return policy, 4 years CRM, 5 years software support, 6 \* 7 \* 24 hours technical support, 12 months warranty.

### 6. Download

OCOM RFID reader SDK: <http://www.possolution.com.cn/cn/download.html>

