Android [] [] [POS   ] [] [] [] [] [M / N [POS-T8 [] ] [] [] [] [] [] [] [] [] [] [] [] [	
RAM / ROM	ROM 4GB eMMC]: RAM 512MB / 1GB DDR2; ]]]]]]micro SD[]]32 GB[]]
	4.0000000000 480 * 800 IPS000
	300000015000000000000000000000000000000
	000000400000
0000	равили стам
	0000050000000000000000000000000000
000	002000000
00	DGPSDDAGPS
000	
	00000000000000000
000	0000
POS	
0000	50
000	DDMSRDDDDISO7811D7812
q	1000001.8V / 3V / 5V0ISO78160000000EMV
0000	]13.56MHz[JISO / IEC 14443 A / B[]]qPBOC
SAM[]	1 SAMQQQQISO7816
0000	0000
000	
0000	WCDMA / GSM
0000	WCDMA 2100MHz[]
	GSM / GPRS / EDGE[]850/900/1800 / 1900MHz[]
WLAN	802.11 A / B / G / N0000
DOCCOOL CONTRACTOR OF THE PROPERTY OF THE PROP	00
WPAN	□□V4.0 + EDR
	NINGER CONTINUES AND
USB()()	DI JACK
0000	
0000 00	00005V - 50000 USB(185232
0000	POSITION TO STATE OF THE POSITION TO STATE OF
	205()QH *82()Q/67()QW *33()Q8
nn	5000000
000	20°C[60°C
000	-40°C]80°C
	10[[]90[RH][][]
0000	1.00000
000000	5000
ESD(()	±8kV0000; ±15kV0000
0000	Android 4.4[][/ SP-UI
0000	SDK
0000	PC]][][]() MDM
	•