

□□□□□□□□□□PDA□□□□

□M / N□OCBs-D5000□

□□

Android 5.1.1
 1GB RAM□8GB ROM
 □□5.0□720 * 1280□□□□□□□□
 □□IP65 / 1.5□□□□
 □□□□□□□□3.7V□8000mAh□□
 □□□□8 MP□□LED□□□□□□□□
 □□4G / Wifi / GPS / □□
 HHW□□□□□□□□
 1D / 2D□□□□□□□□□□
 RFID LF / HF / UHF / NFC□□□□
 TCS1SM□□□□□□□□□□□□□□

□□

□□ □□	
□□	170mm□H□×85mm□W□×23mm□D□±2mm
□□	□ □□□380□□□□□□□□□□
□□	□□□ 5.0□□TFT-LCD□720x1280□□□□□□□□□□
□□	LED □□
□□	3 TP □□□6□□□□□4□□□□□□
□□	2 PSAM□1□SIM□1□TF
□□	□□ □□□□□□3.7V□8000mAh
□□ CHARACTERSTICS	
□□□□□□	□ A531.5GHz□□
□□ □□	Android□ 5.1.1
□□	1GB RAM□8GB ROM□MicroSD□□□32GB□□□
□□ □□	
□□ □□□□	-20°C□50°C
□□ □□□□	-20°C□70°C
□□	5□RH □95□RH□□□□□□
□□ □□□□	5ft./1.5 m□□□□□□□□□□□□□□□□□□
□□	IP65□ IEC□□□□
ESD	±15kv□□□□□□±8kv□□□□□□±8kv□□□□□
□□ □□	
SDK	HHW □□□□□□□□
□□	Java□
□□	Android□ Studio□Eclipse
□□ □□	
WWAN	TDD-LTE□□38,39,40□FDD-LTE□□1,2,3□ 4,7; WCDMA□850/1900 / 2100MHz□□; GSM / GPRS / Edge 850/900/1800 / 1900MHz□;

WLAN	2.4G / 5GDual IEEE 802.11 a / b / g / n / ac	
WPAN	Class v2.1 + EDRv3.0 + HSv4.0	
	GPSA-GPS5	
CAPTUE		
1D	1D	N431x
2D	2DCMOSImager	N6603
		PDF417MicroPDF417RSS TLC-39DatamatrixQR Micro QRAztecMaxiCode PostNet
	8	
	LED	
RFID		
RFID		125KHz / 134.2KHzFDX-B / HDX
		ISO 11784&; 11785
	R / W	2 10
RFID HF		13.56MHz
		ISO 14443A&; 15693
	R / W	2 8
RFID		865868MHz 920925MHz
		EPC C1 GEN2 / ISO 18000-6C
		2DBI
	R / W	1 1.5
2.45GHz		200
433MHz		200
ZigBee		
		IEEE 802.15.4
		100 200
		TCS1SM
		508 DPI
		FRR <0.008 FAR <0.005
		1000
PSAM		
		ISO 7816
		9600 1920038400,43000,56000,57600,115200
		2
		1xPower 1x 1xDC 1xUSB
		UHF