## One of the state o

(M/N:POS-A15/A15-A)

××

	pos-a15/pos-a15-a
□□ board①	□□□ CeleronProcessor J1900 □□2.0GHz
□□ board②	2.0GHz A83T []8[] Cortex-A7 [][]
0S①	Windows7 (□□)
os@	android 5∏1
memory 1	2GB ram 32GB □□□□
memory@	2GB ram 8GB rom
	□ screen15.6 □, □ screen15.6inch
	58mm 00000000000000000000000000000000000

i/o □□ (①J1900)	usb*4
	rj45*1
	rj11*1
	hdmi * 1 ( <u>                                     </u>
	vga*1
	line-out*1 mic-in*1
	DB9 RS232 [] * 1
i/o	rj11*1
	tf [][] * 1
	rj45*1
	hdmi * 1 ()
	usb*2
	DB9 RS232 port*1
	audio*1
	usb otg 🛮
	0°C <u></u> 40°C
□□ □□ (android)	□□, wifi, gps
0 00 (00)	3
	DB9 RS232 port*3, [][][][]
□ □□ (android)	3_/4 _ cammera, lcd, rfid,,,
	-20°Cto 60°C
packingdimension	46 * 43 * 51 🔲
00 000	110-240v/50-60hz [[[[[]]], [[[]]] dc12/5a [[[]]

**×**J1900□□□:

×