

android PDA

D4000

android PDA

n Android5.1

n 1G RAM 8G ROM TF 64GB;

n 28nm ARM Qual-core A53,1.3-1.5GHz

n 4G LTE 3G WCDMA;

n GPS A-GPS

500 LED

SIM PSAM Micro SD TF

n 3.7V 4000mAh;

n 4.0 QVGA

n IP65;

6 1.5m

	157×76×28
	324
	4.0 QVGA TFT-LCD 65×480 * 800 QVGA LED
	SIM Micro SD TF
	USB2.0
	3.7V 4000mAh
	28nm ARM Qual-core A53,1.3-1.5GHz
	1G RAM
Flash ROM	8G NAND Micro SD / TF 64G

IEEE802.11b / g / n	
LTE	FDD-B1 B3 B7 B8 B28 TDD-B38 B39 B40 B41
WCDMA / GSM	WCDMA 850MHZ-824MHZ-849MHZ; 869MHZ-894MHZ 900MHZ-880MHZ-915MHZ; 925MHZ-960MHZ 1800MHZ-1710MHZ-1785MHZ; 1805MHZ-1880MHZ 1900MHZ-1850MHZ-1910MHZ; 1930MHZ-1990MHZ
	2.0 + EDR / 3.0 + HS / 4.1 + HS 5-10m
	-10 50
	-25 70
	0 RH - 95 RH
	6 1.5m
	1000 / 0.5m 6
	IP65
	Android5.1
SDK	
	JAVA
	966 955 N4313
	4Mil
	10000 107640
	104 ± 12 /
	47 ± 35 / 35 ± 3
	UPC / EAN Code128 Code39 Code93 Code11 Interleaved 2 of 5 2 of 5 2 of 5 Codabar MSI RSS
CCD	CCD HONEYWELL N3680
	752 × 480
	9000ft.candles / 96900
VLD	655nm ± 10nm
	PDF417 MicroPDF417 RSS TLC-39 Datamatrix QR Micro QR Aztec MaxiCode; KIX 3
RFID	
HF	13.56MHz; ISO14443A
	500 LED
	A-GPS