

# OCBS-W010 Handheld wired USB laser barcode reader 2.4g bluetooth wireless barcode scanner

## FEATURE:

- 32bit decoding chip
- Up to 200 scans / sec scan rate
- Can scan broken barcodes and screen barcodes
- 2.4GHz communication mode, more flexible and portable
- 16MB huge memory, can store thousands of barcodes
- I USB port can charger and communicate with PC

## Specification

Scanning Performance	
<b>Interface</b>	2.4GHz&USB
<b>decoding speed</b>	200 Times/SEC
<b>Read code system</b>	EAN-13,EAN-8,UPC-A,UPC-E,ISSN,ISBN,Codabar, Code 128,Code 93,ITF-6,ITF-14,Interleaved 2 of 5 Industrial 2 of 5,Matrix 2 of 5,GS1 Databar, Code 39, Code 11,MSI-Plessey,Plessey
<b>Read the precision</b>	≥4mil
<b>The light source</b>	LED (610nm~640nm)
<b>Read the depth of field</b>	Code 39 □5mil□□65mm~175mm EAN-13 (13mil)□55mm~605mm
<b>Barcode sensitivity</b>	incline ±60° @0°Roll and 0°Skew rotate ±30° @0°Pitch and 0°Skew deflection ±60° @0°Roll and 0°Skew
<b>Symbol contrast</b>	≥30% Differences with
Mechanical/electrical Parameters	
<b>Rated power</b>	0.30W
<b>Working voltage</b>	3.2~3.6V DC
<b>Electricity flow</b>	working current 100mA standby current 10uA
<b>The power adapter</b>	input□AC100~240V, 50~60Hz; output :DC 5V ,1000mA
<b>Appearance of size</b>	168mm*93mm*72mm
<b>Heavy volume</b>	198g
Environmental Parameters	
<b>Working temperature</b>	-20°C ~ +60°C
<b>Storage temperature</b>	-40°C ~ +85°C
<b>Working humidity</b>	5% ~ 95% ( No condensation)
<b>Ambient light</b>	0~100□000LUX