

# Supermarkt 360 graden desktop USB Windoes Android robuuste 1d 2d omnidirectionele barcodelezer

(M/N:OCBS-T215)

Functies:



Groot leesvenster;

Identificeer snel de 1D/2D-code van het scherm;

Verborgene anti-trek datakabel aansluiting.

## Specificatie

Algemeen	
Model	OCBS-T215
Koppel	USB
Werkspanning	5V
Huidige starten	420mA
Werk huidige	400mA
Stand-bystroom	270mA

Prestatie	
Sensor	Totale belichting 640*480 CMOS-sensor
Lichtbron	Rode LED
Veldweergave	57,2° (H), 44,2° (V)
Bewegingstolerantie:	> 0.3m/s
Scanhoek	Pitch ±70°@ 0°Roll en 0° Skew Rol 360° @ 0° Pitch en 0° Skew Scheef ±70°@ 0°Roll en 0° Pitch
Symboolcontrast	20% minimaal reflecterend verschil
Immuniteit voor omgevingslicht	0-100.000 Lux
Typische scherptediepte	Code39 (5mil): 20 mm-80 mm, EAN13(13mil):10mm-160mm QR (15mil):10mm-140mm Gegevensmatrix (15 mil): 10 mm-100 mm PDF417 (10mil):10mm-120mm
Decodering vermogen:	(Codabar),(Code 39),(Code 32),(Industriële 2 van 5),(Interleaved 2 van 5),(Standaard 2 van 5),(Matrix 2 van 5),(Code 93),(Code 11 ),(Code 128),(UPC-A),(UPC-E),(EAN/JAN-8),(EAN/JAN-13),(GS1 DataBar(RSS14) (PDF417),(QR-code),(Micro QR),(Data Matrix),(Azteeks),(Hanxi-code)
Fysiek	
Gewicht	Bruto:640g
Pakket	230*170*95mm
Omgeving	
Werktemperatuur en vochtigheid:	0 tot 45 graden Celsius, 10% ~ 80% Geen condensatie
Opslagtemperatuur en vochtigheid:	-20 tot 60 graden Celsius, 10% ~ 90% Geen condensatie

















Model: OCBS-T215

Interface: USB



OCBST2152214100001

Made in China





1. Introduction	1
2. Safety Precautions	2
3. Installation	3
4. Operation	4
5. Troubleshooting	5
6. Appendix	6

**Special Precautions Manual**

1. The device and also its the charging socket  
connections shall be used in the manner. When charging  
applied or plugged into the power supply, and  
the other cases.

2. The device shall not be exposed to a fire, with which  
and a small amount of gasoline can be added to the device,  
and then exposed to fire and flames.

3. Special Precautions: This instruction has been strictly and  
carefully checked and confirmed, but it will have to  
verify the instructions and errors in spelling and  
handwriting with minimum good device will be connected in  
the user manual of the instruction without reserve, the  
copyright of this technology is owned by the company, and  
no other work or technology may modify it.

**THE POWER SUPPLY IS A POWER  
SOURCE, BE CAREFUL IN USING IT.**



Copyright © 2010 by ocom. All rights reserved. This document is a  
proprietary document of ocom. It is confidential. It will be used only for  
the specific purpose of the device. It is not to be distributed or used  
for other purposes and the user shall be held liable for any  
violation of this document. ocom shall not be held liable for any  
damage or loss of data or other consequences resulting from the use  
of this document.





**2D Barcode Scanner**  
Model: OCBS-T215      Color: Black  
Interface: USB  
Power Input: 5V1A      CE FC  
  
OCBS T2152214100001  
Made in China