

## 15.6 inch touch screen pos system Retail

(M/N:POS-A15/A15-A)

### Features:

#### **pos system,touch screen pos system,pos system retail**

Intel CeleronProcessor J1900 Quad core 2.0GHz HighConfiguration CPU for Windows system

2.0GHz A83T ARM 8-Core Cortex-A7 Processor for Android system

2GB RAM+8GB ROM standard (Android)

2GB RAM+32GB SSD standard (Windows)

Multi-point capacitive touch screen

Embedded 58mm or 80mm thermal printer(Optional)

Embedded MSR, RFID reader(Optional)

Stylish display panel

### Applications:

Catering: hotel, restaurant, fast-food restaurant, coffeeshop, bakery and cake shop

Retailer: Business Street, boutique, department store,cosmetics shop and high-class barbershop

Recreation: sauna, spa, night club, theme park, casino andpoint of sales for lottery ticket

Commercial: information management terminals for parking lot,inn, aviation, subway, station and wharf

### Pictureshow:



### Parameter:

Model	POS-A15/POS-A15-A
Main Board①	Intel CeleronProcessor J1900 Quad core 2.0GHz
Main Board②	2.0GHz A83T ARM 8-Core Cortex-A7 Processor
OS①	Windows7(Beta)
OS②	Android 5.1
Memory①	2GB RAM 32GB SSD
Memory②	2GB RAM 8GB ROM
Touch Screen	Multi-point capacitive touch
Screen Size	Main screen15.6 inch,Vice screen15.6inch
Color	Black or White

Printer	58mm big gear thermal printer or 80mm thermal printer with Auto cutter (optional)
I/O port①J1900	USB*4
	RJ45*1
	RJ11*1
	HDMI*1(for vice screen)
	VGA*1
	LINE-OUT*1 MIC-IN*1
	DB9 RS232 port *1
I/O port(②A83T)	RJ11*1
	TF slot *1
	RJ45*1
	HDMI*1(for vice screen)
	USB*2
	DB9 RS232 port*1
	Audio*1
USB OTG port	
Operating temperature	0°C to 40°C
Other Function (Android)	Bluetooth, WIFI,GPS
Optional items(Windows)	I3 I5 CPU, LCD VFD display, RFID, MSR cammera,3G, DB25 parallel port, DB9 RS232 port*3, other size screen
Optional items(Android)	3G/4G cammera, LCD VFD display, RFID,card reader, MSR,other size screen
Storage temperature	-20°Cto 60°C
Packingdimension	46*43*51cm
Power adapter	110-240V/50-60HZ AC power, Input DC12/5A out put



J1900Motherboard Picture:

