

3 inch Android USB thermal POS Receipt printer

(OCP-80G)

Features:

POS printer, pos thermal printer, android pos printer

- 1.Desktop or wall-mounted type for option.
- 2.Supports multi 1D barcodes and QR codes printing.
- 3.100M Ethernet port, ultra high speed data transmission.
- 4.Supports 256KB NV Logo storage and 2M big buffer memory.
- 5.Supports black mark detection and order reminding function, compatible with OPOS driver.
- 6.Supports printing status monitor and anti-losing order function.
- 7.3 interface 260mm/s printing Speed

Parameters:

POS printer, pos thermal printer, android pos printer

Printing method:	Direct thermal
Printing speed:	230mm/s □260mm/s
Roll width:	79.5±0.5mm
Print diameter:	Φ80mm
Paper thickness:	0.06-0.08mm
Column capacity:	576dots/line512 Dots/line
Line's pacing :	3.75mm□Adjustable by commands□
Print command:	Compatible with the ESC/POS command
Interface type:	Serial+USB+Lan/36P parallel port/25P serial +USB/LAN
Cutters life:	1million cuts
Print head life:	100 km
Input buffer :	2048Kbytes
NV Flash:	256Kbytes
Power adaptor:	AC110V/240V□50~60Hz
Power supply:	DC 24V/2.5A
Cash drawer supply:	DC 24V/1A
Work environment:	Temperature(0□45) humidity(10□80%)□Non- condense□
Work environment:	Temperature(0-45) degree centigrade, humidity(10-80%) Non- condense
Storage environment:	Temperature(-10□60℃); Humidity(10□90%)
Character size:	ANK□FontA:1.5*3.0mm/ FontB□1.1*2.1mm
Barcode:	UPC-A/UPC-E/JA□EAN13□JAN8□EAN8/CODE39/ITF /CODE93/CODE128/QRCode/PDF417 (options)
Characters:	PC347□Standard Europe□□Katakana□PC850□Multilingual□□PC860□Portuguese□□PC863 □Canadian-French□□PC865□Nordic□□West Europe□Greek□Hebrew□East Europe□Iran□WPC1252□PC866□Cyrillic#2□□PC852□Latin2□□ PC858□IranII□Latvian□Arabic□PT151□1251□

Physical
characteristics

Weight: 1.25Kg; Appearance size: 190×145×143mm (length * width * height)

Product Show:

POS printer,pos thermal printer,android pos printer







www.ocominc.com

CE FCC





Relevant documents:

[*Specification](#)

[*IP Address Configure Manual](#)

[*Instruction Manual](#)

[*Driver for all windows system](#)

[*Driver for Linux](#)

[*Printer Parameters Setting Tools](#)

*CD Files